cryptsetup Disk encryption

CONCEPTS

luksFormat destroys all data on the device. Double-check the device name with lsblk first.

Block device /dev/sdb1
↓ open
Mapping /dev/mapper/<name>
↓ mount
Filesystem readable data

Without the LUKS header the data is gone for good. Keep a header backup somewhere safe, off the disk itself.

CREATE

cryptsetup luksFormat *<device>*
Encrypt a device with LUKS

OPEN AND CLOSE

cryptsetup open *<device>* *<name>*
Unlock and map a device

cryptsetup close *<name>*
Remove the mapping and wipe the key

cryptsetup status *<name>*
Show an active mapping

cryptsetup open --key-file *<file>* *<device>* *<name>*
Unlock with a key file

cryptsetup open --readonly *<device>* *<name>*
Unlock read-only

KEY SLOTS

cryptsetup luksAddKey *<device>*
Add another passphrase

cryptsetup luksAddKey *<device>* *<keyfile>*
Add a key file

KEY SLOTS (cont.)

cryptsetup luksChangeKey *<device>*
Change a passphrase

cryptsetup luksRemoveKey *<device>*
Remove the passphrase you type

cryptsetup luksKillSlot *<device>* *<slot>*
Remove a slot by number

INSPECT AND HEADER

cryptsetup luksDump *<device>*
Show header, slots and digests

cryptsetup luksUUID *<device>*
Print the UUID

cryptsetup luksHeaderBackup *<device>* **--header-backup-file** *<file>*
Save the header to a file

cryptsetup luksHeaderRestore *<device>* **--header-backup-file** *<file>*
Restore a saved header

blkid *<device>*
Show type crypto_LUKS and UUID

RESIZE

cryptsetup resize *<name>*
Grow mapping to fill the device

resize2fs /dev/mapper/<name>
Grow an ext4 filesystem

BOOT AND FSTAB

echo "<name> **UUID=**<uuid> **none luks" >> /etc/crypttab**
Unlock at boot

echo "/dev/mapper/<name> <dir> **ext4 defaults 0 2" >> /etc/fstab**
Mount after unlock