
LLDB LLVM debugger

CONCEPTS

Compile with -g (and -O0 for sane stepping), otherwise LLDB has no source lines or local variables.



Commands are noun verb (breakpoint set, frame select); most have short aliases such as b, n, s, c, bt, p, f.

START AND ATTACH

lldb *<prog>*
Load a program

lldb -- *<prog> <args>*
Load a program with arguments

lldb -p *<pid>*
Attach to a running process

lldb -c *<core> <prog>*
Inspect a core dump

run [args]
Start the program

process attach --name *<name>*
Attach by process name

settings set target.run-args *<args>*
Set arguments for later runs

settings set target.env-vars *<VAR>=<val>*
Set an environment variable

process detach
Release the process and keep it running

quit
Leave LLDB

BREAKPOINTS

b *<func>*
Break at a function

b *<file>:<line>*
Break at a line of a file

BREAKPOINTS (cont.)

breakpoint set --name *<func>* **--condition '***<cond>***'**
Break only when the condition holds

breakpoint list
List breakpoints and hit counts

breakpoint delete *<n>*
Delete a breakpoint

breakpoint disable *<n>*
Disable a breakpoint

breakpoint enable *<n>*
Re-enable a breakpoint

breakpoint set --func-regex *<regex>*
Break on every function matching a regex

breakpoint set --method *<name>*
Break on a C++ method by base name

breakpoint modify --condition '*<cond>***'** *<n>*
Add or change a condition

WATCHPOINTS

watchpoint set variable *<var>*
Stop when a variable changes

watchpoint set expression -- *<addr>*
Watch the memory at an address

watchpoint list
List watchpoints

watchpoint delete *<n>*
Delete a watchpoint

RUN CONTROL

c
Continue until the next stop

n
Step over the next line

s
Step into the next line

finish
Run until the current function returns

thread until *<line>*
Run to a line in this frame

STACK AND THREADS

bt
Backtrace of the current thread

bt all
Backtrace of every thread

frame select *<n>*
Switch to frame n

up
Go to the caller frame

down
Go back toward the callee frame

thread list
List threads

thread select *<n>*
Switch to thread n

INSPECT DATA

frame variable
Show arguments and locals

frame variable *<var>*
Show one variable

p *<expr>*
Evaluate a C/C++ expression

MEMORY AND REGISTERS

memory read --size 4 --format x --count 4 *<addr>*
Dump four 32-bit words in hex

register read
Show general registers

SOURCE AND SYMBOLS

disassemble --frame
Disassemble the current function

FROM GDB

GDB to LLDB

GDB	LLDB
`break foo`	b foo
`rbreak <re>`	breakpoint set -r <re>
`info locals`	frame variable
`info break`	breakpoint list
`watch <var>`	watchpoint set variable <var>
`info threads`	thread list
`disassemble`	disassemble --frame
`info registers`	register read